

מגן ומייצב מתח AVR PRO

מכשיר להגנה על ציוד רגיש מפני שינויי מתח ורעשים

תכונות:

- מאפשר עבודה גם כאשר יש שינויי מתח רבים.
- היחיד שמאפשר הפעלה מחדשת לאחר פגיעת נחשול מתח / קצר
- היחיד שהוא גן מייצב וגם מגן
- היחיד עם הגנה חזקה במיוחד 1100 ג'אול
- נצילות גבוהה מעל 95%.
- מעגל ייצוב מתח מוצא.
- המעגל נשלט ע"י מעבד IC בעל אמינות גבוהה.
- במקרה של עומס חריג, יתבצע ניתוק אוטומטי, קיים לחצן לצורך הפעלה מחדשת.
- מתאים לכל סוגי הצרכנים הרגישים.
- 2 שקעי מוצא ישראליים.
- תצוגת נוריות לחיווי תפקוד המכשיר.
- הגנה נפרדת למעגל טלפון/מודם/פקס



SPECIFICATIONS

MODEL		AVR 1200N	AVR 2000N
POWER RATING		1200VA/600W	2000VA/1000W
INPUT	Voltage / Frequency	230V +/-20% 50 or 60Hz	
OUTPUT	Voltage / Frequency	230V Typical +/-7% 50 or 60Hz	
EFFICIENCY		95%	
LED INDICATORS	Power ON	Green color LED	
	Stpe power DOWN	Orange color LED	
	Stpe power UP	Orange color LED	
PROTECTION	Spike protection	Varistor 1100 joules	
	Overload protection	Input circuit breaker protection	
	Short Circuit	Input circuit breaker protection	
	Internet communication	√	
	Data phone communucation	RJ11	
PHYSICAL	Net weight (Kg)	1.6	1.8
	Dimension (mm) W x D x H	123 * 136 * 102	
ENVIRONMENT	Ambient operation	3,500 meters max. elevation, 0-95% humidity non-condensing, 0-40°C	
	Audible Noise	<40DbA (1 METER FROM SURFACE)	
	Storage condition	15,000 meters max	
	Storage temperature	-20%°C - 55°C	
	Temperature	0°C - 40°C	

Characteristics subject to change without prior notice